




## Bare Fiber Adapter

<b>Features</b>	
Low insertion loss Good repeatability Easy operation	
<b>Application</b>	
Temporarily connect to bare fiber Fiber testing in lab Production line of optical fiber devices	

### Specifications:

Parameter	FC/SC/ST/LC
Ferrule ID (mm)	0.126 ~ 0.127
Ferrule OD (mm)	2.499 (1.8 for LC)
Insertion Loss (dB)	≤0.02
Repeatability (dB)	≤0.02
Spring Pulling Force (dB)	200g
Fiber Type	Φ125um SM or MM fiber
Plug Times	≥10000
Operation Temperature (°C)	-40 ~ 85

### Ordering Information

Part Number	Description	Photo
BFA-FC-1	FC Bare Fiber Adaptor	
BFA-FC-2	FC Bare Fiber Adaptor	

BFA-SC-1	LC Bare Fiber Adaptor	
BFA-SC-2	LC Bare Fiber Adaptor	
BFA-LC-1	LC Bare Fiber Adaptor	
BFA-ST-1	ST Bare Fiber Adaptor	