

Description

Mi-Wave's 525 series Dial Type Uncalibrated Phase Shifter

Notes

S/N: N/A

Electrical Specifications

	Minimal	Typical	Maximum
Frequency Range	60 GHz		90 GHz
Phase Shifter (degrees)		0-180 degree	
Insertion Loss		0.5 dB	
Average Power			0.7 Watts
VSWR		1.20:1	

Physical Specifications

Input and Output Ports	WR-12 Waveguide, UG-387/UFlange
Flanges	UG-387/U
Housing Material and Finish	Black Anodized Aluminum
Waveguide Material and Finish	Gold Plated Aluminum

Tested by: Kim Madden

Date: 2021-04-05