

Reactel, Incorporated

Reacting First to All Your Filter Needs.

LTE 700 Lower Block A Bandpass Filter

3C9-701-X6N11

Reactel is proud to present this bandpass filter as another member of the growing family of 700 MHz LTE units. This particular unit is suitable for the Lower Block A frequency band and is centered at 701 MHz. Reactel has a large variety of LTE 700 and other wireless band filters and multiplexers; please contact the factory with your specifications.



Specifications

| | |
|------------------|---|
| Center Frequency | 701 MHz |
| Passband | 698 – 704 MHz, minimum |
| Insertion Loss | ≤ 1.0 dB @ Passband |
| Return Loss | ≥ 20 dB @ Passband |
| Attenuation | ≥ 30 dB @ 728 – 894 MHz |
| Connectors | Type N Female in / out |
| Size | 2.25" high x 1.25" wide x 3.3" long, nominal excluding connectors |